

LED Indicators

LED Indicator	Status
Solid Red LED	Charging
LED Off	Fully charged
Flashing Red and Blue	Pairing in Transmitter / Receiver Mode
Flashing Red	Low battery
Solid Blue LED	Successfully paired
Flashing Blue (Every 2 Seconds)	Powered on but not paired with <i>Bluetooth</i> ® devices

Note:

- For first time use, once powered on, the adapter will automatically enter pairing mode. Please follow the instructions below on how to pair.

How to Use Charging

- Connect the micro-USB end of the charging cable to the charging port of the Bluetooth® adapter.
- Plug the USB end of the charging cable to a USB charging port or any active USB port.
- The LED indicator will turn red when charging. It

will automatically turn off when the device is fully charged.

Note:

- You can use the adapter while it is charging.
- We recommend charging the unit for at least 2 hours before using it for the first time.

Pairing

Pair in TX mode:

- Set the TT-BA07 to TX mode and connect it to your audio transmitting device.
- Place your Bluetooth® audio receiving device within a 3 feet / 1 meter range and set it to pairing mode.
- Press and hold the Power Button for 5 seconds (LED indicator flashes blue slowly) and tap twice to enter pairing mode (LED indicator flashes red and blue alternately). After approximately 30 seconds, the pairing will be done (LED indicator in solid blue).

Note:

- In order to achieve low latency, please make sure your receiving Bluetooth device also support **Qualcomm® aptX™ Low Latency** codec, otherwise you may experience noticeable lag between sound and picture.
- Please do not connect TT-BA07 to an amplifier output in TX mode, which may cause over-voltage and damage the adapter.

Pair in RX mode:

Press and hold the Power Button of the adapter for 5 seconds (LED indicator flashes blue slowly). It will start pairing 5 seconds after being powered on (LED indicator flashes red and blue alternately).

- Activate the *Bluetooth*® function on your phone and search for the nearby *Bluetooth*® devices:
 - For iOS: Settings > *Bluetooth*® > On
 - For Android: Settings > Wireless & Networks > *Bluetooth*®: On > Scan for devices
- Find "TaoTronics TT-BA07" in the search results and tap on it to connect. Once connected, the LED indicator will turn solid blue.

Notes:

- The adapter enters pairing mode automatically when powered on for the first time.
- The original pairing memory will be cleared after a mode switch. It will automatically start pairing each time it is powered on.
- If a PIN code is required for pairing, try 0000 (four zeros), 8888 (four eights), 1111 (four ones), or 1234.
- The adapter can remember previously paired devices and will attempt to pair with devices automatically, without going into pairing mode.

- Turn on the Bluetooth® function on your first device. In approximately 30 seconds, the first device will automatically connect in.

Note:

- When you pair with two devices, both can play music at the same time.
- The adapter will automatically re-pair when powered on.

In RX mode:

In RX mode, the adapter is able to pair with two *Bluetooth*® devices at the same time.

- Follow previous instructions in the "Pairing" section to pair the TT-BA07 with your first device. Disable the *Bluetooth*® function on your first device. Tap the Power Button twice to pair with the second device.
- Turn on the *Bluetooth*® of the first device, now TT-BA07 adapter is successfully paired with both devices.

Note:

- Only one device can play music at any time. You have to stop the music on one device to play on the other.
- The adapter will automatically re-pair when powered on.

Pair with two devices at the same time

In TX mode, the adapter is able to pair with two *Bluetooth*® stereo earphones/speakers at the same time.


- Follow the previous instructions in the "Pairing" section to pair the TT-BA07 with your first device.
- Turn off the *Bluetooth*® function on your first device, tap the Power Button twice to pair and connect to your second device.

Care and Maintenance

- Keep the adapter away from heat and humidity.
- Do not expose the adapter to direct sunlight or extreme heat.
- Do not try to take the adapter apart. It may cause serious damage.
- Do not drop or knock the adapter on hard surfaces as it damages the interior circuit.
- Do not use chemicals or detergents to clean the product.
- Do not scrape the surface with sharp objects.

EN

Product Diagram



- ① LED Indicator
 - ② Power Button
 - ③ Transmitter Mode
 - ④ Mode Switch
 - ⑤ Receiver Mode
 - ⑥ 3.5mm Audio Port
 - ⑦ Micro USB Charging Port
- Port

Control Functions

Function	Operation
Power On	When off, press and hold the Power Button for 5 seconds
Power Off	When on, press and hold the Power Button for 5 seconds
Pairing	When powered on, press the Power Button twice to start pairing.
Mode Switch	Slide the Mode Switch to and from TX and RX
Play / Pause	In RX mode, press the Power Button once to play / pause music

Note:

- The mode can only be successfully switched after the adapter is turned off for 3 seconds. After the switch, the pairing history of the previous devices will be cleared.